

Rapid fuse selection table for power regulator

Objective Products : PAC15

CURRENT CAPACITY	ApplicableFuse () = Rating	ApplicableFuse Holder	FUSE MAKER
20A	CR2L-30 (250V,30A : 350A2S/100kA,250V)	CM-2A (3 linkages)	FUJI ELECTRIC CO., LTD.
	CR2LS-30 (250V,30A : 350A2S/100kA,250V)	CM-1A (3 linkages)	FUJI ELECTRIC CO., LTD.
	CS5F-40 (500V,40A : 1000A2S/200kA,500V)	—	FUJI ELECTRIC CO., LTD.
	250GH-32 (250V,32A : 410A2S/100kA,250V)	HT4017	Hinode Electric Co., Ltd.
30A	CR2L-50 (250V,50A : 850A2S/100kA,250V)	CM-2A (3 linkages)	FUJI ELECTRIC CO., LTD.
	CR2LS-50 (250V,50A : 850A2S/100kA,250V)	CM-1A (3 linkages)	FUJI ELECTRIC CO., LTD.
	CS5F-40 (500V,40A : 1000A2S/200kA,500V)	—	FUJI ELECTRIC CO., LTD.
	250GH-40 (250V,40A : 600A2S/100kA,250V)	HT4017	Hinode Electric Co., Ltd.
45A	CR2L-75 (250V,70A : 2300A2S/100kA,250V)	CM-2A (3 linkages)	FUJI ELECTRIC CO., LTD.
	CR2LS-75 (250V,75A : 2300A2S/100kA,250V)	CM-1A (3 linkages)	FUJI ELECTRIC CO., LTD.
	BLC075-1 (550V,75A : 5000A2S/100kA,420V)	AFa100 (Base) Pa100 (Cap)	FUJI ELECTRIC CO., LTD.
	CS5F-75 (500V,75A : 3500A2S/200kA,500V)	—	FUJI ELECTRIC CO., LTD.
	250GH-63 (250V,63A : 1680A2S/100kA,250V)	HT4017	Hinode Electric Co., Ltd.
	350GH-63 (250V,63A : 2220A2S/100kA,250V)	HT4017	Hinode Electric Co., Ltd.
60A	CR2L-100 (250V,100A : 4000A2S/100kA,250V)	CM-2A (3 linkages)	FUJI ELECTRIC CO., LTD.
	CR2LS-100 (250V,100A : 4000A2S/100kA,250V)	CM-1A (3 linkages)	FUJI ELECTRIC CO., LTD.
	BLC090-1 (550V,90A : 11500A2S/100kA,420V)	AFa100 (Base) Pa100 (Cap)	FUJI ELECTRIC CO., LTD.
	CS5F-100 (500V,100A : 5000A2S/200kA,500V)	—	FUJI ELECTRIC CO., LTD.
	250GH-80 (250V,80A : 2800A2S/100kA,250V)	HT4017	Hinode Electric Co., Ltd.
	350GH-80 (250V,80A : 3540A2S/100kA,250V)	HT4017	Hinode Electric Co., Ltd.
80A	CR2L-125 (250V,125A : 6500A2S/100kA,250V)	CM-2A (3 linkages)	FUJI ELECTRIC CO., LTD.
	CS5F-150 (500V,150A : 10000A2S/200kA,500V)	—	FUJI ELECTRIC CO., LTD.
	250GH-125 (250V,125A : 6700A2S/100kA,250V)	HT4017	Hinode Electric Co., Ltd.
	350GH-125 (250V,125A : 6950A2S/100kA,250V)	HT4017	Hinode Electric Co., Ltd.
100A	CR2L-140 (250V,140A : 7000A2S/100kA,250V)	CM-2A (3 linkages)	FUJI ELECTRIC CO., LTD.
	CS5F-150 (500V,100A : 10000A2S/200kA,500V)	—	FUJI ELECTRIC CO., LTD.
	250GH-160 (250V,160A : 9000A2S/100kA,250V)	—	Hinode Electric Co., Ltd.
	350GH-160 (250V,160A : 10950A2S/100kA,250V)	—	Hinode Electric Co., Ltd.